

GOODWE

Cutting-edge hybrid inverter with smart operation modes and powerful back-up capabilities

- ✓ Lower energy cost
- ✓ Smart and flexible solutions
- ✓ Uninterrupted power supply
- ✓ Superb safety and performance

The ET G2 hybrid inverter is designed to maximise energy output, enhance self-consumption, and facilitate extensive back-up power for homeowners. With power rating up to 15kW, intelligent load controls and a wide battery voltage range, the inverter caters to individual needs. To secure a high level of energy autonomy, combine the hybrid inverter with GoodWe HV battery, and connect the system to the GoodWe EV chargers and/or any smart-grid ready household appliances. By combining a variety of smart operation modes, the system can be optimized to further drive down energy cost.



Smart operation modes



Powerful backup



Integrated smart meter

ET G2 Series

Hybrid Inverter | 6 – 15kW | Up to 3 MPPTs | Three Phase | HV

EMEA

Technical Data		GW6000-ET-20	GW8000-ET-20	GW10K-ET-20	GW12K-ET-20	GW15K-ET-20
Battery Input Data						
Battery Type ^{*1}				Li-Ion		
Nominal Battery Voltage (V)				500		
Battery Voltage Range (V)				150 ~ 720		
Start-up Voltage (V)				150		
Number of Battery Input				1		
Max. Continuous Charging Current (A)		30	30	40	40	40
Max. Continuous Discharging Current (A)		30	30	40	40	40
Max. Charging Power (W)		9000	12000	15000	18000	24000
Max. Discharging Power (W)		6600	8800	11000	13200	16500
PV String Input Data						
Max. Input Power (W) ^{*2}		9600	12800	16000	19200	24000
Max. Input Voltage (V) ^{*3,4}				1000		
MPPT Operating Voltage Range (V) ^{*5}				120 ~ 850		
Start-up Voltage (V)				150		
Nominal Input Voltage (V)				620		
Max. Input Current per MPPT (A)				16		
Max. Short Circuit Current per MPPT (A)				24		
Number of MPP Trackers		2	2	3	3	3
Number of Strings per MPPT		1				
AC Output Data (On-grid)						
Nominal Output Power (W)		6000	8000	10000	12000	15000
Nominal Apparent Power Output to Utility Grid (VA)		6000	8000	10000	12000	15000
Max. Apparent Power Output to Utility Grid (VA) ^{*6}		6000	8000	10000	12000	15000
Max. Apparent Power from Utility Grid (VA)		12000	16000	20000	20000	20000
Nominal Output Voltage (V)		400 / 380, 3L / N / PE				
Output Voltage Range (V) ^{*7}		170 ~ 290				
Nominal AC Grid Frequency (Hz)		50 / 60				
AC Grid Frequency Range (Hz)		45 ~ 65				
Max. AC Current Output to Utility Grid (A) ^{*8}		8.7	11.6	14.5	17.4	21.7
Max. AC Current From Utility Grid (A)		15.7	21.0	26.1 ^{*9}	26.1 ^{*9}	26.1 ^{*9}
Power Factor		0.8 leading~0.8 lagging				
Max. Total Harmonic Distortion		<3%				
AC Output Data (Back-up)						
Back-up Nominal Apparent Power (VA)		6000	8000	10000	12000	15000
Max. Output Apparent Power without Grid (VA) ^{*10}		6000 (12000 @60sec)	8000 (16000 @60sec)	10000 (18000 @60sec)	12000 (18000 @60sec)	15000 (18000 @60sec)
Max. Output Apparent Power with Grid (VA)		6000	8000	10000	12000	15000
Max. Output Current (A)		13.0 (17.4 @60sec)	17.4 (23.3 @60sec)	21.7 (26.1 @60sec)	21.7 (26.1 @60sec)	21.7 (26.1 @60sec)
Nominal Output Voltage (V)		400 / 380				
Nominal Output Frequency (Hz)		50 / 60				
Output THDv (@Linear Load)		<3%				
Efficiency						
Max. Efficiency		98.0%	98.0%	98.2%	98.2%	98.2%
European Efficiency		97.2%	97.2%	97.5%	97.5%	97.5%
Max. Battery to AC Efficiency		97.2%	97.5%	97.5%	97.5%	97.5%
MPPT Efficiency		99.5%				
Protection						
PV Insulation Resistance Detection				Integrated		
PV AFCI3.0				Optional		
Residual Current Monitoring				Integrated		
PV Reverse Polarity Protection				Integrated		
Battery Reverse Polarity Protection				Integrated		
Anti-islanding Protection				Integrated		
AC Overcurrent Protection				Integrated		
AC Short Circuit Protection				Integrated		
AC Overvoltage Protection				Integrated		
DC Switch				Integrated		
DC Surge Protection				Type II		
AC Surge Protection				Type II		
Remote Shutdown				Integrated		
General Data						
Operating Temperature Range (°C)				-35 ~ +60		
Relative Humidity				0 ~ 100%		
Max. Operating Altitude (m)				4000		
Cooling Method				Natural Convection		
User Interface				LED, WLAN + APP		
Communication with BMS				RS485, CAN		
Communication with Meter				RS485		
Communication with Portal				WiFi + LAN + Bluetooth		
Weight (kg)		23	23	25	25	25
Dimension (W × H × D mm)		496 × 460 × 221				
Topology		Non-isolated				
Ingress Protection Rating		IP66				
Mounting Method		Wall Mounted				

*1: The Li-Ion battery usually contain two mainstream type: LFP and Ternary Lithium battery.

*2: Max. input power, not continuous for 1.6*normal power. Besides, in Australia, for most of the PV modules, the max. input power can reach 2*Pn, for example, the max. input power of GW6000-ET-20 can reach 12000W.

*3: For 1000V system, the maximum operating voltage is 950V.

*4: When the input voltage ranges from 975V to 1000V, the inverter will enter the standby mode, and the voltage returns to 975V to enter the normal operation state.

*5: Please refer to the user manual for the MPPT Voltage Range at Nominal Power.

*6: According to the local grid regulation.

*7: Output Voltage Range: phase voltage.

*8: When the three-unbalance function is activated, the Max. AC Current Output to the on-grid load can reach 13A, 17.4A, 21.7A, 21.7A and 21.7A respectively.

*9: If the inverter is installed with the 3x25A AC breaker, it is suggested that the consumption and feed-in AC power should be less than 11040W (0.8x0.8x25x230x3), and this limitation can be set by SolarGo App.

*10: Can be reached only if PV and battery power is enough.

*: Please visit GoodWe website for the latest certificates.